

4in1 Generator - Welder Compressor - Light Tower

Welder

Rated Duty Cycle	0,5
Open Circuit Voltage	DC75V
Welding Current Range	50-200A
Rated Current/Voltage	180A / 27.2V
Welding Wires	Yes, 3M Long
Welding Rod	1.6-5.0mm

Compressor

Tank Volume	20L
Flow Capacity	100L/min
Pressure Rang	0.6-0.8MPA
Stage	1

Light Tower

Lighting Lamp	LED / 4x100W
Luminous Flux	80-100lm/W

Features

Long Life Overhead Valve Engine

Electric / Self Start for easy operate

Low-Oil Shutdown To Prevent Engine Damage

High Performance Alternator

Hardened Steel Tube Chassis

Circuit Breaker Protected Outlets

Low Tone Muffler

Multi-Funtions:Generator, Welder, Air Compressor,
Lighting Tower

Generator

Rated Output Watts	5000W
Maximum Output Watts	5500W
Power Factor	1
Rated Voltage	220V
Frequency	50Hz
Alternator Winding	100% Copper Winding
Engine Model	Kohler, Command PRO CH440
Engine Displacement	429cc / 14HP
Bore x Stroke/mm	89x69
Engine Type	4 Stroke, Air Cooled, OHV
Engine RPM	3000 RPM
Lubrication Method	Splash Sump
Digital Meter	YES
Starting Method	Electric Key Start
Battery	YES
Battery Size	12AH
Low Oil Shutdown	YES
Fuel gauge	Yes - In Tank
Fuel Tank Capacity (Litters)	30L
Wheel	YES

